

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type
								10V	4.5V	2.5V	1.8V				
								Freq=1MHz							

联系人: 何 TEL: 13590313572 QQ: 310793799

Dual-NMOS

1	VS6808DH	Dual-N	YES	20	±8	0.4~1.2	6	--	18	25	44	410	90	80	SOT23-6L
2	VS8810DTS	Dual-N	YES	20	±8	0.4~1.2	7	--	19	26	--	415	90	80	TSSOP8
3	VSA007N02ED	Dual-N	YES	20	±12	0.5~1.2	12	--	6.5	9	--				PDFN5x6
4	VSA007N02KD	Dual-N	NO	20	±12	0.4~1.0	13	--	7.4	9.4	--	1225	200	170	PDFN5x6
5	VS4812DS	Dual-N	NO	30	±20	1.0~2.5	6	23	32	--	--				SOP8
6	VS3640DS	Dual-N	NO	30	±20	1.0~2.5	9	16	24	--	--	455	75	60	SOP8
7	VS3622DS	Dual-N	NO	30	±20	1.3~2.4	12	10	14	--	--	890	140	100	SOP8
8	VS3640DE	Dual-N	NO	30	±20	1.3~2.4	24	15	24	--	--	460	75	55	PDFN3333
9	VS3640DP	Dual-N	NO	30	±20	1.3~2.4	30	14	22	--	--	450	75	60	PDFN5x6
10	VSP018N03MD	Dual-N	NO	30	±20	1.0~2.2	30	17	23	--	--				PDFN5x6
11	VS3622DE	Dual-N	NO	30	±20	1.3~2.4	35	10	14	--	--	880	140	110	PDFN3333
12	VS3622DP	Dual-N	NO	30	±20	1.3~2.4	40	8.7	12	--	--	890	140	105	PDFN5x6
13	VS3622DP2	Dual-N	NO	30	±20	1.3~2.4	42	7.5	11	--	--	895	140	100	PDFN5x6
14	VSO026N04MD	Dual-N	NO	40	±20	1.0~2.5	7	23	27.5	--	--	775	90	60	SOP8
15	VSO040N04MD	Dual-N	NO	40	±20	1.0~2.5	6	32	38	--	--	315	45	35	SOP8
16	VS4640DE	Dual-N	NO	40	±20	1.1~2.3	20	26	39	--	--	485	45	35	PDFN3333
17	VSO060N06MD	Dual-N	NO	60	±20	1.0~3.0	5	38	45	--	--				SOP8
18	VSO100N10MD	Dual-N	NO	100	±20	1.0~2.5	3.7	76	81	--	--	555	40	35	SOP8

Dual-PMOS

19	VS4805DS	Dual-P	NO	-30	±20	-1.0~-2.5	-8	18	28	--	--				SOP8
20	VSO010P03MD	Dual-P	NO	-30	±20	-1.0~-2.5	-10	13	16	--	--	2260	340	280	SOP8
21	VSO011P03MD	Dual-P	NO	-30	±20	-1.0~-2.5	-13	11	15	--	--	2540	330	290	SOP8
22	VSP011P03MD	Dual-P	NO	-30	±20	-1.0~-2.5	-18	11	15	--	--	2540	330	290	PDFN5x6
23	VSO200P06MD	Dual-P	NO	-60	±20	-1.0~-3.0	-3.4	130	160	--	--	500	30	20	SOP8
24	VSO100P06MD	Dual-P	NO	-60	±20	-1.0~-3.0	-4.6	70	85	--	--	940	55	40	SOP8

联系人: 何 TEL: 13590313572 QQ: 310793799

Asymmetric-NMOS

25	VS3622DB	NMOS	NO	30	±20	1.3~2.4	28	8.2	11	--	--	890	140	105	DFN3x3
		NMOS	NO	30	±20	1.3~2.4	30	6	8.4	--	--	1175	180	130	

NMOS+PMOS

26	VSO035M03MD	NMOS	NO	30	±20	0.6~1.8	8	18	24	--	--	415	75	60	SOP8
		PMOS	NO	-30	±20	-0.6~-1.8	-7.6	25	30	--	--	1090	140	100	
27	VSO025C03MC	NMOS	NO	30	±20	1.3~2.4	10	15	23	--	--	460	75	60	SOP8
		PMOS	NO	-30	±20	-1.3~-2.4	-8	23	38	--	--	860	140	95	
28	VSD010C03MC	NMOS	NO	30	±20	1.0~2.5	30	10	13	--	--	880	110	95	TO-252-4L
		PMOS	NO	-30	±20	-1.0~-2.5	-22	24	40	--	--	950	115	105	
29	VSP008C03MD	NMOS	NO	30	±20	1.0~2.5	45	6.5	10	--	--	1140	180	135	PDFN5x6
		PMOS	NO	-30	±20	-1.0~-2.5	-35	13	24	--	--	2605	300	230	
30	VSO050M04MD	NMOS	NO	40	±20	1.0~2.5	6	32	40	--	--	320	45	35	SOP8
		PMOS	NO	-40	±20	-1.0~-2.5	-5	50	60	--	--	835	85	65	
31	VSO030C04MC	NMOS	NO	40	±20	1.8~3.2	8	18	24	--	--	840	90	75	SOP8
		PMOS	NO	-40	±20	-1.0~-2.5	-6	32	38	--	--	1520	155	110	
32	VSD030C04MC	NMOS	NO	40	±20	1.8~3.2	31	18	24	--	--	840	90	75	TO-252-4L
		PMOS	NO	-40	±20	-1.0~-2.5	-22	32	38	--	--	1520	155	110	
33	VSO100M06MD	NMOS	NO	60	±20	1.0~3.0	4.5	70	85	--	--	270	35	25	SOP8
		PMOS	NO	-60	±20	-1.0~-3.0	-4.5	75	90	--	--	980	50	35	
34	VS4559MS	NMOS	NO	60	±20	1.0~3.0	8	35	55	--	--				SOP8
		PMOS	NO	-60	±20	-1.0~-3.0	-7.5	75	95	--	--				

联系人: 何 TEL: 13590313572 QQ: 310793799

Single-NMOS

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type			
								10V	4.5V	2.5V	1.8V					Freq=1MHz		
35	VS2302AT	NMOS	NO	20	±12	0.4~1.0	3.2	--	30	40	--				SOT23			
36	VS2300AC	NMOS	NO	20	±12	0.5~1.5	5.2	--	25	30	--				SOT23			
37	VS8810AL	NMOS	YES	20	±12	0.5~1.0	6	--	15	17.5	21				SOT23-3L			
38	VS2018AL	NMOS	NO	20	±12	0.5~1.2	6	--	20	24	30				SOT23-3L			
39	VS3416AC	NMOS	YES	20	±8	0.4~1.2	6.5	--	17	23	35	450	110	100	SOT23			
40	VS3416AL	NMOS	YES	20	±8	0.4~1.2	7	--	15	19	24				SOT23-3L			
41	VS2622AA	NMOS	NO	20	±12	0.4~1.0	45	--	8.2	10	--	1170	195	165	DFN2x2			
42	VSE005N02KS	NMOS	NO	20	±12	0.3~1.1	59	--	4.6	6	8.7	2525	295	380	PDFN3333			
43	VS003N02LS	NMOS	NO	20	±8	0.3~1.2	60	--	3.6	4.6	--	4380	490	440	TDFN3.3X3.3			
44	VSE004N02KS	NMOS	NO	20	±12	0.4~1.0	72		3.6	4.5	6	3690	610	530	PDFN3333			
45	VS003N02MS	NMOS	NO	20	±20	1.0~2.5	84	3	3.8			3550	1035	1015	TDFN3.3X3.3			
46	VSE008NE2LS	NMOS	NO	25	±12	0.6~1.5	55	5.8	6.6	--	--	1560	170	125	PDFN3333			
47	VS3640BC	NMOS	NO	30	±12	0.6~1.2	5	--	29	36	--	770	50	45	SOT23			
48	VS3400BC	NMOS	NO	30	±12	0.6~1.2	5.8	--	27	35	--				SOT23			
49	VS3400BL	NMOS	NO	30	±12	0.6~1.2	5.8	--	27	35	--				SOT23-3L			
50	VS3640AC	NMOS	NO	30	±20	1.0~2.5	6	19	27	--	--	455	75	55	SOT23			
51	VSO018N03MS	NMOS	NO	30	±20	0.7~2.0	8	17	22	--	--	415	75	60	SOP8			
52	VS3618AH	NMOS	NO	30	±20	1.0~2.5	8	9.5	13	--	--	1105	180	135	SOT23-6L			
53	VS3640AS	NMOS	NO	30	±20	1.0~2.5	11	14	22	--	--	455	75	60	SOP8			
54	VS3622AS	NMOS	NO	30	±20	1.3~2.4	15	8.4	12	--	--	835	135	105	SOP8			
55	VSO012N03MS	NMOS	NO	30	±20	0.8~2.2	15	9	12	--	--				SOP8			
56	VS3618AS	NMOS	NO	30	±20	1.3~2.4	16	6.6	9.6	--	--	1130	180	135	SOP8			
57	VS3640AE	NMOS	NO	30	±20	1.0~2.5	25	13.5	23	--	--	455	75	60	PDFN3333			
58	VS3640AD	NMOS	NO	30	±20	1.3~2.4	28	16	24	--	--	465	75	55	TO-252			
59	VSI018N03MS	NMOS	NO	30	±20	1.0~2.2	30	16	22	--	--	415	75	60	TO-251SL			
60	VSD018N03MS	NMOS	NO	30	±20	1.0~2.2	30	16	22	--	--	415	75	60	TO-252			
61	VSE018N03MS	NMOS	NO	30	±20	0.9~2.0	30	16	20	--	--	415	75	60	PDFN3333			
62	VS012N03MS	NMOS	NO	30	±20	0.8~2.2	38	9	12	--	--				TDFN3.3X3.3			
63	VS3622AE	NMOS	NO	30	±20	1.0~2.5	45	7.9	12	--	--	860	140	105	PDFN3333			
64	VS3622AA	NMOS	NO	30	±20	1.3~2.4	45	8.8	13	--	--	865	150	110	DFN2x2			
65	VS3618AE	NMOS	NO	30	±20	1.0~2.5	50	6	9	--	--	1110	180	130	PDFN3333			
66	VS3618AP	NMOS	NO	30	±20	1.0~2.5	54	5.4	8.4	--	--	1110	180	130	PDFN5x6			
67	VS3622AD	NMOS	NO	30	±20	1.0~2.5	55	8	12	--	--	845	135	105	TO-252			
68	VSE006N03MS	NMOS	NO	30	±20	1.0~2.5	58	5.4	7.4	--	--	1595	185	160	PDFN3333			
69	VSI012N03MS	NMOS	NO	30	±20	0.8~2.5	60	9	12	--	--				TO-251			
70	VSD012N03MS	NMOS	NO	30	±20	0.8~2.5	60	9	12	--	--				TO-252			
71	VS3610AE	NMOS	NO	30	±20	1.0~2.5	64	4	5.7	--	--	1930	310	260	PDFN3333			
72	VS004N03LS	NMOS	NO	30	±12	0.6~1.5	65	--	4.7	6.5	--				TDFN3.3X3.3			
73	VS3090BD	NMOS	NO	30	±20	1.0~2.5	68	5.5	7.5	--	--	1550	190	160	TO-252			
74	VS3610AP	NMOS	NO	30	±20	1.0~2.5	70	3.7	5.4	--	--	1930	310	260	PDFN5x6			
75	VS3618AD	NMOS	NO	30	±20	1.3~2.4	70	5.8	9	--	--	1110	180	130	TO-252			
76	VS3698AE	NMOS	NO	30	±20	1.0~2.5	76	3	4.4	--	--	2530	380	295	PDFN3333			
77	VSE005N03MS	NMOS	NO	30	±20	1.0~2.5	78	2.8	4.2	--	--	2530	380	295	PDFN3333			
78	VS3610AI	NMOS	NO	30	±20	1.3~2.4	85	4.2	6	--	--	1930	310	260	TO-251			
79	VS3610AD	NMOS	NO	30	±20	1.0~2.5	85	4.3	6	--	--	1930	310	260	TO-252			
80	VS3080AP	NMOS	NO	30	±20	1.2~2.8	90	4	5.5	--	--				PDFN5x6			
81	VS3080AI	NMOS	NO	30	±20	1.0~3.0	90	4	5.5	--	--				TO-251			
82	VS3080AD	NMOS	NO	30	±20	0.6~1.8	90	4	5.5	--	--				TO-252			
83	VS3606AE	NMOS	NO	30	±20	1.0~2.5	92	2.5	3.4	--	--	3635	550	520	PDFN3333			
84	VSP005N03MS	NMOS	NO	30	±20	1.0~2.5	105	2.7	4.1	--	--	2530	380	295	PDFN5x6			
85	VSD005N03MS	NMOS	NO	30	±20	1.0~2.5	105	3	4.4	--	--	2525	380	290	TO-252			
86	VS3698AP	NMOS	NO	30	±20	1.0~2.5	105	3.1	4.5	--	--	2530	380	295	PDFN5x6			

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type	
								10V	4.5V	2.5V	1.8V					Freq=1MHz
87	VS3698AD	NMOS	NO	30	±20	1.0~2.5	105	3.1	4.5	--	--	2530	380	295	TO-252	
88	VS3606AP	NMOS	NO	30	±20	1.0~2.5	106	2	2.9	--	--	3650	550	520	PDFN5x6	
89	VS3606AD	NMOS	NO	30	±20	1.0~2.5	110	2.6	3.5	--	--	3650	550	520	TO-252	
90	VS3606AT	NMOS	NO	30	±20	1.3~2.4	140	3	4	--	--	3455	535	480	TO-220AB	
91	VS3606ATD	NMOS	NO	30	±20	1.3~2.4	140	3	4	--	--	3455	535	480	TO-263	
92	VS30150AD	NMOS	NO	30	±20	1.0~2.5	175	2	2.5	--	--	6550	900	795	TO-252	
93	VS3604AT	NMOS	NO	30	±20	1.3~2.4	180	2.1	2.8	--	--	4565	785	710	TO-220AB	
94	VSC045N04MS	NMOS	NO	40	±20	1.0~2.5	4	36	42	--	--				SOT23	
95	VS4640AC	NMOS	NO	40	±20	1.3~2.4	5	29	44	--	--	485	45	35	SOT23	
96	VSO040N04MS	NMOS	NO	40	±20	1.0~2.5	6	35	40	--	--	320	45	35	SOP8	
97	VS4618AH	NMOS	NO	40	±20	1.3~2.4	8	14	20	--	--	1300	105	85	SOT23-6L	
98	VSO026N04MS	NMOS	NO	40	±20	1.0~2.5	10	22	26.5	--	--				SOP8	
99	VSO013N04MS	NMOS	NO	40	±20	1.0~2.5	13	11	13	--	--	1180	160	120	SOP8	
100	VS4618AS	NMOS	NO	40	±20	1.0~2.5	14	10.5	17	--	--	1315	100	80	SOP8	
101	VSO007N04MS	NMOS	NO	40	±20	1.0~2.5	16	5.7	6.7	--	--	2370	275	190	SOP8	
102	VS4610AS	NMOS	NO	40	±20	1.3~2.4	17	6.3	10	--	--	2100	170	130	SOP8	
103	VS4020AS	NMOS	NO	40	±20	1.0~2.5	18	6	7.5	--	--				SOP8	
104	VSO006N04MS	NMOS	NO	40	±20	1.0~2.5	20	3.7	4.7	--	--	4390	400	355	SOP8	
105	VSB022N04MS	NMOS	NO	40	±20	1.0~2.2	20	18	21	--	--				TDFN3.3X3.3	
106	VSI040N04MS	NMOS	NO	40	±20	1.0~3.0	20	36	42	--	--	320	45	35	TO-251SL	
107	VSD040N04MS	NMOS	NO	40	±20	1.0~3.0	20	36	42	--	--	320	45	35	TO-252	
108	VSD026N04MS	NMOS	NO	40	±20	1.0~3.0	30	19	22	--	--				TO-252	
109	VSB013N04MS	NMOS	NO	40	±20	1.0~2.2	40	9	11	--	--				TDFN3.3X3.3	
110	VS4618AE	NMOS	NO	40	±20	1.3~2.4	43	10	15	--	--	1295	100	80	PDFN3333	
111	VS4618AP	NMOS	NO	40	±20	1.3~2.4	45	9.6	15	--	--	1290	100	85	PDFN5x6	
112	VS4610AB	NMOS	NO	40	±20	1.3~2.4	53	7.2	11	--	--	2015	170	110	TDFN3.3X3.3	
113	VS4610AE	NMOS	NO	40	±20	1.3~2.4	55	6.8	10	--	--	2015	170	110	PDFN3333	
114	VS4610AP	NMOS	NO	40	±20	1.3~2.4	60	6.6	10	--	--	2035	170	110	PDFN5x6	
115	VSP007N04MS	NMOS	NO	40	±20	1.0~2.5	62	5.5	6.6	--	--	2370	275	190	PDFN5x6	
116	VS4610AD	NMOS	NO	40	±20	1.3~2.4	65	6.6	10	--	--	2060	175	130	TO-252	
117	VSD007N04MS	NMOS	NO	40	±20	1.0~2.5	70	5.6	6.7	--	--	2370	275	190	TO-252	
118	VSI007N04MS	NMOS	NO	40	±20	1.0~2.5	70	5.6	6.7	--	--	2370	275	190	TO-251	
119	VS4020AP	NMOS	NO	40	±20	1.3~2.5	80	4.5	5.5	--	--	3915	300	255	PDFN5x6	
120	VS4080AI	NMOS	NO	40	±20	1.0~2.5	80	5	6	--	--				TO-251	
121	VS4080AD	NMOS	NO	40	±20	1.0~2.5	80	5	6	--	--				TO-252	
122	VSP006N04MS	NMOS	NO	40	±20	1.0~2.5	110	3.3	4.3	--	--	4290	400	355	PDFN5x6	
123	VS40200AP	NMOS	NO	40	±20	1.2~2.8	120	2.4	--	--	--				PDFN5x6	
124	VS40200AD	NMOS	NO	40	±20	1.2~2.8	120	2.4	3.4	--	--				TO-252	
125	VS4604AP	NMOS	NO	40	±20	1.3~2.4	125	2.7	3.7	--	--	5015	440	380	PDFN5x6	
126	VS4604AD	NMOS	NO	40	±20	1.3~2.4	140	2.8	3.8	--	--	5200	400	390	TO-252	
127	VS40200BT	NMOS	NO	40	±20	1.0~2.5	140	4	4.5	--	--	5695	595	490	TO-220AB	
128	VS4604AT	NMOS	NO	40	±20	1.0~2.5	150	2.6	3.7	--	--	5140	445	390	TO-220AB	
129	VS4604ATD	NMOS	NO	40	±20	1.0~2.5	150	2.6	3.7	--	--	5140	445	390	TO-263	
130	VST006N04MS	NMOS	NO	40	±20	1.0~3.0	180	3.5	4.3	--	--	4440	395	340	TO-220AB	
131	VS40200AT	NMOS	NO	40	±20	1.2~2.4	200	2.5	3.5	--	--	6605	550	440	TO-220AB	
132	VS40200ATD	NMOS	NO	40	±20	1.2~2.4	200	2.3	3.3	--	--	6605	550	440	TO-263	
133	VS4602AP	NMOS	NO	40	±25	2.4~3.9	220	1.6	--	--	--	9260	720	400	PDFN5x6	
134	VS40230ATD	NMOS	NO	40	±20	2.2~3.9	230	2.2	--	--	--				TO-263	
135	VS40230AT	NMOS	NO	40	±20	2.2~3.9	230	2.2	--	--	--				TO-220AB	
136	VS40280AT	NMOS	NO	40	±20	1.0~3.0	280	1.8	--	--	--				TO-220AB	
137	VS4604DT	NMOS	NO	40	±20	1.3~2.4	285	1.7	2.3	--	--	10565	880	740	TO-220AB	
138	VS4604DM	NMOS	NO	40	±20	1.3~2.4	290	1.6	2.2	--	--	10515	890	760	TO-263	
139	VS40300AT	NMOS	NO	40	±20	2.0~4.0	300	1.9	--	--	--				TO-220AB	

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type
								10V	4.5V	2.5V	1.8V				
								Freq=1MHz							
140	VS4603DM6	NMOS	NO	40	±20	1.3~2.4	320	1.3	1.8	--	--	13210	1085	925	TO-263-6L
141	VS4030AS	NMOS	NO	45	±20	1.3~2.5	20	4.5	5.6	--	--	4285	280	145	SOP8
142	VS4604BT	NMOS	NO	45	±20	1.3~2.4	150	2.8	4	--	--	4650	425	280	TO-220AB
143	VS5814AS	NMOS	NO	55	±20	1.3~2.4	11	14	20	--	--	1270	95	60	SOP8
144	VS5812AS	NMOS	NO	55	±20	1.0~3.0	12	9.5	13.5	--	--	1030	105	85	SOP8
145	VS6016AS	NMOS	NO	55	±20	1.0~2.5	12	11	12	--	--	2250	220	165	SOP8
146	VS5810AS	NMOS	NO	55	±20	1.0~3.0	15	6.8	9.5	--	--	1545	155	130	SOP8
147	VS5808AS	NMOS	NO	55	±20	1.0~2.5	18	4.8	7	--	--	2625	205	195	SOP8
148	VS5804AS	NMOS	NO	55	±20	1.3~2.5	20	2.9	4	--	--	3970	405	380	SOP8
149	VS5804BS	NMOS	NO	55	±20	1.3~2.4	20	3.9	4.8	--	--	6395	395	335	SOP8
150	VS5806AS	NMOS	NO	55	±20	1.0~2.5	20	4.5	5.2	--	--	3500	315	295	SOP8
151	VS5812AI	NMOS	NO	55	±20	1.0~2.5	40	9.5	13.5	--	--	1030	105	85	TO-251
152	VS5812AE	NMOS	NO	55	±20	1.0~2.5	40	10	14.5	--	--	1030	105	85	PDFN3333
153	VS5812AP	NMOS	NO	55	±20	1.0~2.5	42	9.5	13.5	--	--	1030	105	85	PDFN5x6
154	VS5812AD	NMOS	NO	55	±20	1.0~2.5	50	9.5	13.5	--	--	1030	105	85	TO-252
155	VS5806AP	NMOS	NO	55	±20	1.0~2.5	86	4.3	5	--	--	3500	315	295	PDFN5x6
156	VS5804AP	NMOS	NO	55	±20	1.0~3.0	105	2.7	3.9	--	--	3970	405	380	PDFN5x6
157	VS5804AT	NMOS	NO	55	±20	1.0~2.5	139	3.6	4.2	--	--	4950	360	330	TO-220AB
158	VS6640AC	NMOS	NO	60	±20	1.3~2.4	2.8	71	89	--	--	505	30	20	SOT23
159	VS6640AL	NMOS	NO	60	±20	1.3~2.4	3.2	69	85	--	--	505	30	20	SOT23-3L
160	VSC080N06MS	NMOS	NO	60	±16	1.0~3.0	3	70	85	--	--				SOT23
161	VSL080N06MS	NMOS	NO	60	±16	1.0~3.0	3	70	85	--	--				SOT23-3L
162	VSR080N06MS	NMOS	NO	60	±16	1.0~3.0	4	70	85	--	--				SOT89
163	VS6622AL	NMOS	NO	60	±20	1.3~2.4	4.5	38	46	--	--	970	50	35	SOT23-3L
164	VSR050N06MS	NMOS	NO	60	±20	1.0~3.0	6	30	38	--	--				SOT89
165	VSL045N06MS	NMOS	NO	60	±20	1.0~2.5	6	38	45	--	--				SOT23-3L
166	VS6622AS	NMOS	NO	60	±20	1.3~2.4	7	34	41	--	--	970	50	35	SOP8
167	VSO045N06MS	NMOS	NO	60	±20	1.0~2.5	7	36	42	--	--				SOP8
168	VS6640AR	NMOS	NO	60	±20	1.3~2.4	9	67	84	--	--	510	30	20	SOT89
169	VS6412ASL	NMOS	NO	60	±20	1.3~2.4	10	14.5	16	--	--	1240	95	85	SOP8
170	VS6016HS	NMOS	NO	60	±20	1.0~2.5	12	11	12	--	--				SOP8
171	VS6410AS	NMOS	NO	60	±20	1.3~2.4	12	11	12	--	--	2015	135	115	SOP8
172	VSO011N06MS	NMOS	NO	60	±20	1.0~2.5	12	11	12.8	--	--	3975	170	135	SOP8
173	VSO012N06MS	NMOS	NO	60	±20	1.3~2.3	12	11	12.8	--	--	3975	170	135	SOP8
174	VSO012N06MS	NMOS	NO	60	±20	1.0~3.0	13	9.5	11.5	--	--	1905	205	180	SOP8
175	VSO010N06MS	NMOS	NO	60	±20	1.0~2.5	14	9	11	--	--	3970	170	135	SOP8
176	VS6020AO	NMOS	NO	60	±20	1.0~3.0	15	7.3	9	--	--	2270	205	195	SOP8
177	VS6408AS	NMOS	NO	60	±20	1.3~2.4	15	7.8	9.3	--	--	2820	195	155	SOP8
178	VSI080N06MS	NMOS	NO	60	±16	1.0~3.0	15	68	85	--	--				TO-251SL
179	VSD080N06MS	NMOS	NO	60	±16	1.0~3.0	15	68	85	--	--				TO-252
180	VSO008N06MS	NMOS	NO	60	±20	1.0~3.0	16	7.5	8.8	--	--	3400	310	280	SOP8
181	VSO007N06MS	NMOS	NO	60	±20	1.2~2.4	18	6	7	--	--	3485	370	275	SOP8
182	VS6018AS	NMOS	NO	60	±20	1.0~3.0	18	7	8	--	--	3000	295	275	SOP8
183	VSO005N06MS	NMOS	NO	60	±20	1.2~2.4	19	4.5	5.3	--	--	3675	350	340	SOP8
184	VS6406AS	NMOS	NO	60	±20	1.0~3.0	19	5.8	6.7	--	--	4220	285	240	SOP8
185	VS6404BS	NMOS	NO	60	±20	1.3~2.4	20	4.5	5.4	--	--	6045	340	265	SOP8
186	VS6019AS	NMOS	NO	60	±20	1.0~3.0	20	5.5	6.5	--	--	2800	290	250	SOP8
187	VS6038AD	NMOS	NO	60	±20	1.0~2.5	25	35	--	--	--				TO-252
188	VS6622AD	NMOS	NO	60	±20	1.0~2.5	25	36	43	--	--	990	50	35	TO-252
189	VS6614AD	NMOS	NO	60	±20	1.0~2.5	30	26	29	--	--	1310	70	50	TO-252
190	VS6412APL	NMOS	NO	60	±20	1.2~2.5	31	14.5	16	--	--	1240	95	85	PDFN5x6
191	VS6412AEL	NMOS	NO	60	±20	1.2~2.5	33	15	17	--	--	1240	95	85	PDFN3333
192	VS6412ADL	NMOS	NO	60	±20	1.2~2.4	40	14	18	--	--	995	95	85	TO-252

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type				
								10V	4.5V	2.5V	1.8V					Freq=1MHz			
193	VS6412AIL	NMOS	NO	60	±20	1.2~2.4	40	14	18	--	--	995	95	85	TO-251				
194	VSB012N06MS	NMOS	NO	60	±20	1.0~2.5	44	9.5	11	--	--				TDFN3.3X3.3				
195	VSB011N06MS	NMOS	NO	60	±20	1.3~2.4	50	9	11	--	--	3865	175	135	TDFN3.3X3.3				
196	VST012N06MS	NMOS	NO	60	±20	1.0~2.5	55	8.4	9.8	--	--	1905	205	180	TO-220AB				
197	VST012N06HS	NMOS	NO	60	±20	2.0~3.2	55	8.5	--	--	--				TO-220AB				
198	VSM012N06HS	NMOS	NO	60	±20	2.0~3.2	55	8.5	--	--	--				TO-263				
199	VSD012N06MS	NMOS	NO	60	±20	1.0~2.5	55	8.5	10	--	--	1905	205	180	TO-252				
200	VSD012N06HS	NMOS	NO	60	±20	2.0~3.2	55	8.5	--	--	--				TO-252				
201	VS6065AI	NMOS	NO	60	±20	1.0~2.5	65	7	8	--	--	3750	275	230	TO-251				
202	VS6065AD	NMOS	NO	60	±20	1.0~2.5	65	7	8	--	--	3750	275	230	TO-252				
203	VS6070AD	NMOS	NO	60	±20	2.0~4.0	70	6.5	--	--	--				TO-252				
204	VS6020AP	NMOS	NO	60	±20	1.0~3.0	70	7.2	8.8	--	--	2270	205	195	PDFN5X6				
205	VSP009N06MS	NMOS	NO	60	±20	1.0~3.0	80	6.5	8	--	--	3000	295	275	PDFN5X6				
206	VS6406AP	NMOS	NO	60	±20	1.0~3.0	83	5.7	6.6	--	--	4220	285	240	PDFN5x6				
207	VST007N06HS	NMOS	NO	60	±20	2.0~4.0	85	5	--	--	--				TO-220AB				
208	VSP007N06MS	NMOS	NO	60	±20	1.2~2.5	85	5	6	--	--				PDFN5x6				
209	VSI007N06MS	NMOS	NO	60	±20	1.2~2.5	85	5	6	--	--				TO-251				
210	VSD007N06MS	NMOS	NO	60	±20	1.2~2.5	85	5	6	--	--				TO-252				
211	VS6404AP	NMOS	NO	60	±20	1.0~2.5	95	4.6	5.3	--	--	5425	350	310	PDFN5x6				
212	VS6406AT	NMOS	NO	60	±20	1.3~2.4	110	5.7	6.4	--	--	3905	285	250	TO-220AB				
213	VSP005N06MS	NMOS	NO	60	±20	1.0~3.0	125	3.8	4.9	--	--	4980	505	450	PDFN5X6				
214	VST003N06MS	NMOS	NO	60	±20	1.0~2.5	125	4.4	5.2	--	--	4940	500	495	TO-220AB				
215	VST003N06HS	NMOS	NO	60	±20	2.0~4.0	140	3.7	--	--	--	5220	570	380	TO-220AB				
216	VSM003N06HS	NMOS	NO	60	±20	2.0~4.0	140	3.7	--	--	--	5220	570	380	TO-263				
217	VSD003N06HS	NMOS	NO	60	±20	2.0~4.0	140	4	--	--	--	5220	570	380	TO-252				
218	VSI003N06HS	NMOS	NO	60	±20	2.0~4.0	140	4	--	--	--	5220	570	380	TO-251				
219	VSP003N06HS	NMOS	NO	60	±20	2.0~4.0	140	4.4	--	--	--	5220	570	380	PDFN5x6				
220	VS6018BS	NMOS	NO	65	±20	1.0~2.5	17	6.7	7.9	--	--	5070	260	240	SOP8				
221	VS6412AE	NMOS	NO	65	±20	1.0~2.5	30	19	22	--	--	1240	95	85	PDFN3333				
222	VS6018BD	NMOS	NO	65	±20	1.3~2.4	85	6.5	8.4	--	--	5015	245	195	TO-252				
223	VS6888BT	NMOS	NO	65	±20	2.0~4.0	88	5.3	--	--	--	3720	340	190	TO-220AB				
224	VS6888BTD	NMOS	NO	65	±20	2.0~4.0	88	5.3	--	--	--	3720	340	190	TO-263				
225	VS6018BTD	NMOS	NO	65	±20	1.3~2.4	95	6.3	7.6	--	--	5080	250	205	TO-263				
226	VS6880AT	NMOS	NO	68	±25	2.5~3.9	105	6.1	--	--	--	5855	250	175	TO-220AB				
227	VSD007N07MS	NMOS	NO	70	±20	1.0~3.0	65	6.3	7.5	--	--	3000	250	205	TO-252				
228	VST008N07HS	NMOS	NO	70	±20	2.0~4.0	65	7.5	--	--	--				TO-220AB				
229	VSD008N07HS	NMOS	NO	70	±25	2.0~4.0	65	7.5	--	--	--				TO-252				
230	VSM008N07HS	NMOS	NO	70	±25	2.0~4.0	83	7.3	--	--	--	3330	275	230	TO-263				
231	VS7085AT	NMOS	NO	70	±20	2.0~4.0	90	5.5	--	--	--				TO-220AB				
232	VSP007N07MS	NMOS	NO	75	±20	1.0~3.0	65	5.8	7	--	--	3000	250	205	PDFN5X6				
233	VS7580AT	NMOS	NO	75	±20	2.0~4.0	83	6.5	--	--	--				TO-220AB				
234	VSO012N08MS	NMOS	NO	80	±20	1.0~2.5	12	12	13	--	--	5225	195	165	SOP8				
235	VSO013N08MS	NMOS	NO	80	±20	1.0~3.0	14	10	12	--	--				SOP8				
236	VSO013N08HS	NMOS	NO	80	±20	2.0~4.0	14	10	--	--	--				SOP8				
237	VSR080N08LS	NMOS	NO	80	±16	0.5~1.6	15	55	57	--	--	685	50	40	SOT89				
238	VSO010N08MS	NMOS	NO	80	±20	1.0~3.0	16	8	9	--	--				SOP8				
239	VS8404AS	NMOS	NO	80	±20	1.0~3.0	17	5.2	6.5	--	--	4130	285	255	SOP8				
240	VSO007N07MS	NMOS	NO	80	±20	1.0~3.0	17	8	9	--	--	3000	250	205	SOP8				
241	VSE080N08LS	NMOS	NO	80	±16	0.7~1.6	18	55	57	--	--	570	50	35	PDFN3333				
242	VSP012N08MS	NMOS	NO	80	±20	1.3~2.4	52	12	13	--	--	5375	195	165	PDFN5x6				
243	VSD012N08MS	NMOS	NO	80	±20	1.3~2.4	60	12	13	--	--	5355	200	170	TO-252				
244	VSP013N08MS	NMOS	NO	80	±20	1.0~3.0	66	9	11	--	--				PDFN5X6				
245	VS8066AT	NMOS	NO	80	±20	2.0~4.0	66	9	--	--	--				TO-220AB				

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type				
								10V	4.5V	2.5V	1.8V					Freq=1MHz			
246	VS8066AD	NMOS	NO	80	±20	2.0~4.0	66	9	--	--	--				TO-252				
247	VS8066ATD	NMOS	NO	80	±20	2.0~4.0	66	9	--	--	--				TO-263				
248	VSI013N08MS	NMOS	NO	80	±20	1.0~3.0	66	10	12	--	--				TO-251				
249	VSD013N08MS	NMOS	NO	80	±20	1.0~3.0	66	10	12	--	--				TO-252				
250	VS8068AD	NMOS	NO	80	±20	1.3~2.5	68	9	--	--	--				TO-252				
251	VSD010N08MS	NMOS	NO	80	±20	1.0~3.0	70	7	8	--	--				TO-252				
252	VSI007N07MS	NMOS	NO	80	±20	1.2~2.4	70	9.3	10	--	--	4350	220	180	TO-251				
253	VS8068ATD	NMOS	NO	80	±20	1.3~2.3	70	12	13	--	--	5045	195	165	TO-263				
254	VSP010N08MS	NMOS	NO	80	±20	1.0~3.0	75	7.5	8.5	--	--				PDFN5X6				
255	VST010N08HS	NMOS	NO	80	±20	2.0~4.0	75	7.5	--	--	--				TO-220AB				
256	VST007N07MS	NMOS	NO	80	±20	1.3~2.3	80	8	9	--	--	4420	225	195	TO-220AB				
257	VS80N08AT	NMOS	NO	80	±20	2.0~4.0	83	6.8	--	--	--				TO-220AB				
258	VS80N08ATD	NMOS	NO	80	±25	2.4~3.6	105	7.2	--	--	--	4110	395	255	TO-263				
259	VS80N08AN	NMOS	NO	80	±25	2.0~4.0	105	7.2	--	--	--	4110	395	255	TO-262				
260	VSD006N08MS	NMOS	NO	80	±20	1.0~3.0	85	5.8	7	--	--	5205	400	370	TO-252				
261	VS7580ATD	NMOS	NO	80	±25	2.0~4.0	100	6.4	--	--	--	3900	345	275	TO-263				
262	VS80110AT	NMOS	NO	80	±20	2.0~4.0	110	5.5	--	--	--				TO-220AB				
263	VS80110ATD	NMOS	NO	80	±20	2.0~4.0	110	5.5	--	--	--				TO-263				
264	VS150N08BT	NMOS	NO	80	±25	2.0~4.0	155	4.5	--	--	--				TO-220AB				
265	VS150N08BN	NMOS	NO	80	±25	2.0~4.0	155	4.5	--	--	--				TO-262				
266	VS150N08BTD	NMOS	NO	80	±25	2.0~4.0	155	4.5	--	--	--				TO-263				
267	VSH160N10MS	NMOS	NO	100	±20	1.3~2.4	2.2	153	162	--	--	280	30	20	SOT23-6L				
268	VSC160N10MS	NMOS	NO	100	±20	1.0~3.0	2.6	150	165	--	--				SOT23				
269	VSL100N10MS	NMOS	NO	100	±20	1.0~2.5	3	78	85	--	--	525	40	35	SOT23-3L				
270	VSR160N10MS	NMOS	NO	100	±20	1.0~3.0	4	155	165	--	--				SOT89				
271	VSZ090N10MS	NMOS	NO	100	±20	1.0~2.5	5	70	75	--	--	525	40	35	SOT223				
272	VSR090N10MS	NMOS	NO	100	±20	1.0~2.5	5	70	75	--	--	525	40	35	SOT89				
273	VSO100N10MS	NMOS	NO	100	±20	1.0~2.5	6	78	85	--	--	525	40	35	SOP8				
274	VS1H12AS	NMOS	NO	100	±20	1.0~3.0	7	32	35	--	--				SOP8				
275	VS1H16AS	NMOS	NO	100	±20	1.0~3.0	8.2	21	22	--	--				SOP8				
276	VS1H18AS	NMOS	NO	100	±20	1.0~3.0	9	14.5	16.5	--	--				SOP8				
277	VSO025N10MS	NMOS	NO	100	±20	1.0~2.2	9	20	22	--	--				SOP8				
278	VSO014N10MS	NMOS	NO	100	±20	1.0~2.5	10	15	16	--	--	6570	210	190	SOP8				
279	VSO013N10MS	NMOS	NO	100	±20	1.0~3.0	12	11	12.5	--	--				SOP8				
280	VST090N10MS	NMOS	NO	100	±20	1.0~3.0	15	72	76			525	40	35	TO-220AB				
281	VSI090N10MS	NMOS	NO	100	±20	1.0~3.0	15	78	82	--	--	525	40	35	TO-251				
282	VSD090N10MS	NMOS	NO	100	±20	1.0~3.0	15	78	82	--	--	525	40	35	TO-252				
283	VSO008N10MS	NMOS	NO	100	±20	1.3~2.3	17	6.4	10	--	--	1720	1250	75	SOP8				
284	VS40N10AD	NMOS	NO	100	±20	1.0~3.0	25	32	--	--	--				TO-252				
285	VS40N10AT	NMOS	NO	100	±20	1.0~3.0	28	32	--	--	--				TO-220AB				
286	VSD025N10MS	NMOS	NO	100	±20	1.0~2.2	32	20	22	--	--				TO-252				
287	VSD025N10HS	NMOS	NO	100	±20	2.0~4.0	32	20	--	--	--				TO-252				
288	VSF018N10MS	NMOS	NO	100	±20	1.0~3.0	37	14	15	--	--	3040	195	125	TO-220F				
289	VSP018N10MS	NMOS	NO	100	±20	1.0~3.0	42	14	16.5	--	--				PDFN5x6				
290	VS1H42AI	NMOS	NO	100	±20	1.0~3.0	42	14	16.5	--	--				TO-251				
291	VS1H42AD	NMOS	NO	100	±20	1.0~3.0	42	14	16.5	--	--				TO-252				
292	VSP014N10MS	NMOS	NO	100	±20	1.3~2.4	50	16	17	--	--	6525	205	175	PDFN5x6				
293	VSP013N10MS	NMOS	NO	100	±20	1.0~3.0	52	11	12	--	--				PDFN5x6				
294	VSI013N10MS	NMOS	NO	100	±20	1.0~3.0	52	11	12	--	--				TO-251				
295	VSD013N10MS	NMOS	NO	100	±20	1.0~3.0	52	11	12	--	--				TO-252				
296	VST018N10HS	NMOS	NO	100	±20	2.0~4.0	60	13.8	--	--	--	3380	195	165	TO-220AB				
297	VST018N10MS	NMOS	NO	100	±20	1.0~3.0	60	14	15	--	--	3040	195	125	TO-220AB				
298	VST013N10MS	NMOS	NO	100	±20	1.0~2.5	75	11	12	--	--	3630	245	160	TO-220AB				

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type
								10V	4.5V	2.5V	1.8V				
								Freq=1MHz							
299	VSP008N10MS	NMOS	NO	100	±20	1.2~2.3	85	6	10	--	--	1720	1100	75	PDFN5x6
300	VST008N10MS	NMOS	NO	100	±20	1.3~2.5	105	5.7	7	--	--	2630	1130	100	TO-220AB
301	VST008N10HS	NMOS	NO	100	±20	2.2~3.6	105	6.2	--	--	--	1850	1085	80	TO-220AB
302	VST010N10MS	NMOS	NO	100	±20	1.0~3.0	105	8.6	9.5	--	--	5290	340	295	TO-220AB
303	VS4410ATD	NMOS	NO	100	±20	2.0~4.0	110	6	--	--	--				TO-263
304	VS4410AT	NMOS	NO	100	±20	2.0~4.0	110	6.5	--	--	--				TO-220AB
305	VS4410BT	NMOS	NO	100	±25	2.0~4.0	127	6.7	--	--	--	4090	470	310	TO-220AB
306	VS4410BTD	NMOS	NO	100	±25	2.0~4.0	127	6.7	--	--	--	4090	470	310	TO-263
307	VS4310AT	NMOS	NO	100	±20	2.0~4.0	130	5.5	--	--	--				TO-220AB
308	VS4310ADT	NMOS	NO	100	±20	2.0~4.0	130	5.5	--	--	--				TO-247
309	VS4310ATD	NMOS	NO	100	±20	2.0~4.0	130	5.5	--	--	--				TO-263
310	VS4110AT	NMOS	NO	100	±20	2.0~4.0	180	4.5	--	--	--				TO-220AB
311	VS4110ADT	NMOS	NO	100	±20	2.0~4.0	180	4.5	--	--	--				TO-247
312	VS4110ATD	NMOS	NO	100	±20	2.0~4.0	180	4.5	--	--	--				TO-263
313	VSO009N10MS	NMOS	NO	110	±20	1.0~3.0	15	6.6	8.8	--	--	2760	1310	35	SOP8
314	VSP009N10MS	NMOS	NO	110	±20	1.0~3.0	85	6.5	8	--	--	2760	1310	35	PDFN5X6
315	VST009N10MS	NMOS	NO	110	±20	1.3~2.4	108	6.5	8	--	--	2745	1165	35	TO-220AB
316	VST012N12MS	NMOS	NO	120	±20	1.0~3.0	63	11.5	13	--	--	3910	305	230	TO-220AB
317	VSM012N12MS	NMOS	NO	120	±20	1.0~3.0	63	11.5	13	--	--	3910	305	230	TO-263
318	VSP012N12MS	NMOS	NO	120	±20	1.0~3.0	63	12.8	13.8	--	--	3910	305	230	PDFN5X6
319	VSL280N15MS	NMOS	NO	150	±20	1.0~3.0	1.5	230	235	--	--	855	105	30	SOT23-3L
320	VSZ280N15MS	NMOS	NO	150	±20	1.0~3.0	3	230	235	--	--	560	30	25	SOT223
321	VSO280N15MS	NMOS	NO	150	±20	1.0~3.0	3	230	235	--	--	855	105	30	SOP8
322	VSD280N15MS	NMOS	NO	150	±20	1.0~3.0	5	245	240	--	--	560	30	25	TO-252
323	VSO140N15MS	NMOS	NO	150	±20	1.0~3.0	6	125	115	--	--				SOP8
324	VSD140N15MD	NMOS	NO	150	±20	1.3~2.4	10	125	115	--	--				TO-252
325	VST012N15HS	NMOS	NO	150	±25	3.0~5.0	100	11.2	--	--	--				TO-220AB
326	VS7N65AD	NMOS	NO	650	±30	2.4~3.5	7	1100	--	--	--	1065	85	10	TO-252
327	VS7N65AI	NMOS	NO	650	±30	2.4~3.5	7	1100	--	--	--	1065	85	10	TO-251SL
328	VS7N65AT	NMOS	NO	650	±30	2.4~3.5	7	1100	--	--	--	1055	90	10	TO-220AB
329	VS7N65AF	NMOS	NO	650	±30	2.4~3.5	7	1100	--	--	--	1070	85	15	TO-220F

联系人: 何 TEL: 13590313572 QQ: 310793799


Single-PMOS

330	VSB004P02KS	PMOS	NO	-12	±8	-0.4~-1.0	-65	--	4.8	6	--	6580	2065	2060	TDFN3.3X3.3
331	VS2301BC	PMOS	NO	-20	±12	-0.6~-1.5	-1.8	--	95	130	--				SOT23
332	VS3415AC	PMOS	YES	-20	±8	-0.5~-1.0	-5	--	30	40	60				SOT23
333	VS3415AL	PMOS	YES	-20	±8	-0.4~-1.0	-5	--	30	40	60				SOT23-3L
334	VS2522AL	PMOS	NO	-20	±12	-0.4~-1.0	-6	--	25	34	--	1630	170	140	SOT23-3L
335	VSB006P02LS	PMOS	NO	-20	±8	-0.5~-1.2	-50	--	7	9	--				TDFN3.3X3.3
336	VSE003P02KS	PMOS	NO	-20	±12	-0.4~-1.0	-65	--	5.8	8	12	6340	725	615	PDFN3333
337	VSP002P02KS	PMOS	NO	-20	±12	-0.4~-1.0	-90	--	4.3	5.9	8.1	8285	1140	1020	PDFN5x6
338	VS3540AC	PMOS	NO	-30	±12	-0.5~-1.2	-3.4	52	62	81	--	805	60	50	SOT23
339	VSC040P03MS	PMOS	NO	-30	±12	-0.5~-1.5	-4.7	45	55	--	--				SOT23
340	VSO038P03MS	PMOS	NO	-30	±16	-0.5~-2.0	-6	40	50	--	--				SOP8
341	VS4435AS	PMOS	NO	-30	±20	-1.0~-2	-7.8	18	25	--	--	1380	165	110	SOP8
342	VSO030P03LS	PMOS	NO	-30	±20	-0.5~-1.5	-8	23	28	--	--	1090	140	100	SOP8
343	VS4407BS	PMOS	NO	-30	±20	-1.0~-2.5	-10	16	21	--	--	1520	235	180	SOP8
344	VS3518AS	PMOS	NO	-30	±20	-1.0~-2.5	-10	18	31.5	--	--	1510	185	140	SOP8
345	VS3508AS	PMOS	NO	-30	±20	-1.0~-2.5	-13	8.5	15	--	--	3320	395	245	SOP8
346	VS4407AS	PMOS	NO	-30	±20	-1.0~-2.5	-13	11	15	--	--				SOP8
347	VS3510AS	PMOS	NO	-30	±20	-1.0~-2.5	-14	11	18	--	--	1915	300	210	SOP8
348	VSO006P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-15	6.2	8.5	--	--	5215	750	650	SOP8

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type				
								10V	4.5V	2.5V	1.8V					Freq=1MHz			
349	VSO008P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-15	8	11	--	--				SOP8				
350	VSO004P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-18	5	7	--	--				SOP8				
351	VS3506AS	PMOS	NO	-30	±20	-1.2~-2.3	-19	5.7	8.6	--	--	3765	550	400	SOP8				
352	VS3504AS	PMOS	NO	-30	±20	-1.0~-2.4	-20	5	7.1	--	--	5090	750	530	SOP8				
353	VS3522AE	PMOS	NO	-30	±20	-1.3~-2.4	-27	22	39	--	--	850	140	95	PDFN3333				
354	VS3522AA	PMOS	NO	-30	±20	-1.3~-2.4	-30	22	37	--	--	850	140	95	DFN2x2				
355	VSE018P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-34	14	18.5	--	--	1565	240	185	PDFN3333				
356	VSE008P03MS	PMOS	NO	-30	±20	-1.0~-2.2	-35	7.5	10.5	--	--				PDFN3333				
357	VSB012P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-36	10	14	--	--				TDFN3.3X3.3				
358	VS3510AE	PMOS	NO	-30	±20	-1.0~-2.5	-37	12	24	--	--	2565	300	220	PDFN3333				
359	VS30P39AP	PMOS	NO	-30	±20	-1.0~-2.0	-39	9	--	--	--				PDFN5x6				
360	VS30P39AE	PMOS	NO	-30	±20	-1.0~-2.0	-39	10	--	--	--				PDFN3333				
361	VS3510AP	PMOS	NO	-30	±20	-1.3~-2.4	-45	10	17	--	--	1870	300	200	PDFN5X6				
362	VS3508AE	PMOS	NO	-30	±20	-1.0~-2.5	-47	8.5	15	--	--	3320	395	245	PDFN3333				
363	VS30P50AP	PMOS	NO	-30	±20	-1.0~-2.5	-50	4.5	6	--	--				PDFN5x6				
364	VS3508AP	PMOS	NO	-30	±20	-1.3~-2.5	-50	8.8	16	--	--	3305	395	260	PDFN5x6				
365	VS3510AD	PMOS	NO	-30	±20	-1.0~-2.5	-50	12	23	--	--	2555	290	200	TO-252				
366	VS3506AE	PMOS	NO	-30	±20	-1.0~-2.5	-60	6	10	--	--	4725	550	495	PDFN3333				
367	VS30P60AD	PMOS	NO	-30	±20	-1.0~-2.5	-60	10	14	--	--				TO-252				
368	VSD006P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-70	5	7.2	--	--	5215	750	650	TO-252				
369	VS3506AD	PMOS	NO	-30	±20	-1.0~-2.5	-70	6.5	10	--	--	4750	545	490	TO-252				
370	VS3506AP	PMOS	NO	-30	±20	-1.2~-2.3	-75	5.3	8.4	--	--	3770	545	395	PDFN5X6				
371	VSD004P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-80	4.2	6	--	--				TO-252				
372	VSP004P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-80	4.2	6	--	--				PDFN5X6				
373	VST004P03MS	PMOS	NO	-30	±20	-1.0~-2.5	-80	4.2	6	--	--				TO-220AB				
374	VS30P90AD	PMOS	NO	-30	±20	-1.0~-2.5	-90	4.2	6	--	--				TO-252				
375	VS3504AP	PMOS	NO	-30	±20	-1.0~-2.4	-95	4.7	7	--	--	4885	735	485	PDFN5X6				
376	VS3506ATD	PMOS	NO	-30	±20	-1.2~-2.3	-100	6	9	--	--	3810	545	400	TO-263				
377	VS3504AD	PMOS	NO	-30	±20	-1.0~-2.5	-115	5	7.2	--	--	4900	725	460	TO-252				
378	VS3503AP	PMOS	NO	-30	±20	-1.2~-2.3	-120	3.6	5.6	--	--	6315	1010	830	PDFN5X6				
379	VS3503AD	PMOS	NO	-30	±20	-1.2~-2.3	-130	3.9	5.9	--	--	6400	1015	875	TO-252				
380	VS4540AC	PMOS	NO	-40	±20	-1.3~-2.4	-3	68	112	--	--	510	50	40	SOT23				
381	VS4518AH	PMOS	NO	-40	±20	-1.3~-2.4	-5.5	29	44	--	--	1310	115	90	SOT23-6L				
382	VS4518AS	PMOS	NO	-40	±20	-1.0~-2.5	-8	26	39	--	--	1315	110	90	SOP8				
383	VSD050P04MS	PMOS	NO	-40	±20	-1.0~-2.5	-14	42	55	--	--	835	85	65	TO-252				
384	VS4504AS	PMOS	NO	-40	±20	-1.3~-2.4	-18	6.8	10	--	--	5130	490	380	SOP8				
385	VS4518AD	PMOS	NO	-40	±20	-1.3~-2.4	-33	26	42	--	--	1310	115	90	TO-252				
386	VSD025P04MS	PMOS	NO	-40	±20	-1.0~-2.5	-35	25	31	--	--	1675	155	105	TO-252				
387	VSD014P04MS	PMOS	NO	-40	±20	-1.0~-2.5	-55	13.5	16.5	--	--	3000	320	210	TO-252				
388	VS4504AD	PMOS	NO	-40	±20	-1.3~-2.4	-90	7	10	--	--	5120	490	415	TO-252				
389	VSC180P06MS	PMOS	NO	-60	±20	-1.0~-3.0	-2.1	140	170	--	--	500	30	20	SOT23				
390	VSI080P06MS	PMOS	NO	-60	±20	-1.0~-2.5	-15	70	83	--	--	940	55	40	TO-251				
391	VSD080P06MS	PMOS	NO	-60	±20	-1.0~-2.5	-15	70	83	--	--	940	55	40	TO-252				
392	VS6522AD	PMOS	NO	-60	±20	-1.3~-2.4	-18	69	119	--	--	890	55	40	TO-252				
393	VSD035P06MS	PMOS	NO	-60	±20	-1.0~-3.0	-30	26	32	--	--	2535	130	75	TO-252				
394	VSP020P06MS	PMOS	NO	-60	±20	-1.0~-3.0	-65	10	13	--	--	6430	340	310	PDFN5x6				
395	VSD020P06MS	PMOS	NO	-60	±20	-1.0~-3.0	-70	10	13	--	--	6430	340	310	TO-252				
396	VSM007P06MS	PMOS	NO	-60	±20	-1.0~-2.5	-80	8	10	--	--	6985	450	290	TO-263				
397	VSP007P06MS	PMOS	NO	-60	±20	-1.0~-2.5	-80	8	10	--	--	6985	450	290	PDFN5x6				
398	VST007P06MS	PMOS	NO	-60	±20	-1.0~-2.5	-80	8.5	10.5	--	--	6985	450	290	TO-220AB				
399	VSD007P06MS	PMOS	NO	-60	±20	-1.0~-2.5	-80	9	11	--	--	6985	450	290	TO-252				
400	VSC600P10MS	PMOS	NO	-100	±20	-1.0~-3.0	-1.3	485	520	--	--	490	25	15	SOT23				
401	VSZ260P10MS	PMOS	NO	-100	±20	-1.0~-2.5	-2.2	250	260	--	--	960	40	25	SOT223				

NO.	Part ID	Type	ESD	BVDS S [V]	BVGS [V]	VTH [V]	ID [A]	RDON Typ * [mohm] @VGS=				Ciss	Coss	Crss	Package Type
								10V	4.5V	2.5V	1.8V				
								Freq=1MHz							
402	VSO100P10MS	PMOS	NO	-100	±20	-1.0~-2.5	-4	88	92	--	--	2575	90	75	SOP8
403	VSD260P10MS	PMOS	NO	-100	±20	-1.2~-2.3	-10	243	257	--	--	930	40	20	TO-252
404	VSD100P10MS	PMOS	NO	-100	±20	-1.0~-2.5	-17	92	95	--	--	2575	90	75	TO-252
405	VST050P10MS	PMOS	NO	-100	±20	-1.0~-3.0	-25	44	46	--	--				TO-220AB
406	VSD050P10MS	PMOS	NO	-100	±20	-1.0~-3.0	-25	45	48	--	--				TO-252
407	VSI050P10MS	PMOS	NO	-100	±20	-1.0~-3.0	-25	45	48	--	--	5430	245	175	TO-251
408	VSD040P10MS	PMOS	NO	-100	±20	-1.0~-3.0	-30	36	38	--	--	6590	225	175	TO-252
409	VSP040P10MS	PMOS	NO	-100	±20	-1.0~-3.0	-30	36	38	--	--	6590	225	175	PDFN5x6
410	VSD045P10MS	PMOS	NO	-100	±20	-1.3~-2.4	-35	46	51	--	--	4585	180	105	TO-252
411	VST030P10MS	PMOS	NO	-100	±20	-1.0~-2.5	-55	25	28	--	--	7410	310	185	TO-220AB
412	VSM030P10MS	PMOS	NO	-100	±20	-1.0~-2.5	-55	25	28	--	--	7410	310	185	TO-263
413	VSD030P10MS	PMOS	NO	-100	±20	-1.0~-2.5	-55	26	29	--	--	7410	310	185	TO-252
414	VSP030P10MS	PMOS	NO	-100	±20	-1.0~-2.5	-55	26	29	--	--	7410	310	185	PDFN5x6

联系人: 何 TEL: 13590313572 QQ: 310793799



Vanguard Semiconductor

* More products details in www.vgsemi.com